Light controller

10 relay-controlled outputs

Configurable output:

Features

- Normal mode general purpose light; input toggles light
- Timer (auto off) mode transitional lights; often used in combination with a presence sensor
- Configurable input:
 - Normal (toggle push-button)
 - $\circ\,$ Timer reload (extended time for staircase lighting)
 - $\circ\,$ Momentary (output is active while input is pressed used for doorbell)
 - $\circ\,$ Presence or door sensor (sensor activates light, use timer mode for auto off)
 - $\circ\,$ Scene set (no direct light action)
- Smart restart after power supply interruption
- Stand alone / HIQ expansion
- PC, smartphone and cloud connectivity

Model number:	LC-10-IQ mk2
Mounting:	DIN rail, 6M, 106 mm
Dimensions:	106×108×58 mm

Applications

- general purpose discrete (ON/OFF) lights
- automatic corridor and stairs lights
- door-bell
- managed sockets
- bathroom and other single speed fans
- managed appliances (boiler, oven, electric cooker, ...)



General description

The discrete light controller LC-10-IQ is HIQ intelligent expansion module primarily used for controlling discrete (non-dimmable) lights. Featuring high power relay output, it can control other consumers too (mains sockets, heaters, fans,..). LC-10-IQ can be used as stand-alone or part of the integrated system, when connected to one of HIQ Home Controller. Many features are available in the stand alone mode, while advanced features like scenes, scheduling, smartphone operation, internet connection are only available when connected to the appropriate Home Controller.


Output mode



on/off mode button turns the light on and off

timer mode button turns light on, and it automatically goes off after the predefined time

Input mode



Input mode defines how input affect the output. Basic functions are handled internally by light controller, night mode and ready light are handled with master controller.

Technical specification

Output power per relay	
- incandescent / halogen 230V	800 W
- halogen 12 V with transformer	400 W
- LED with transformer or compact	400 W
- fluorescent with electronic ballast	400 W
- parallel compensated fluo lamps	250 W / 30 uF
- electric heater (any resistive load)	1400 W
Total output power per group:	2800 W
Maximum input cable length:	50 m
Power supply:	24 V / max. 145 mA
Ingress protection:	IP20
Operating temperature:	045 °C
Storage temperature:	-2075 °C
Relative humidity:	095 % n/c
Weight:	250g

Terminals

H_{o}° H_{o}° H_{o}° H_{o}°	$H_{0}^{\circ} = H_{0}^{\circ} H_{0}^{\circ} = H_{0}^$
+24V 0V IX0 C IX1 IX2 C IX3 19 20 21 22 23 24 25 26 27	IX4 C IX5 IX6 C IX7 IX8 C IX9 28 29 30 31 32 33 34 35 36
HIQ	▲ C€
LC-10-IQ Light controller	
1 2 3 4 5 6 7 8 9 L QX0 QX1 QX2 QX3 L1	10 11 12 13 14 15 16 17 18 QX4 QX5 QX6 QX7 QX8 QX9
L° × × × × × × × × × × × × × × × × × × ×	

From: http://wiki.hiq-home.com/ -

Permanent link: http://wiki.hiq-home.com/doku.php?id=en:hiq_hw:lc-10-iq-mk2

Last update: 2024/11/27 06:45

