

Motion sensor

Microwave detector on wall or ceiling



| | |
|---------------|------------------|
| Model number: | MW-A18-LC |
| Connects to: | digital input |
| Mounting: | Wall or ceiling |
| Dimensions: | 94mm x 42mm |

Applications

- Motion detector
- Ready light
- Lighting control
- Hotel GRMS

Features

- Aestetical look
- Easy mount

Installation instruction

- Ensure that there are no obstructions (plants, screens, furniture etc.) in the field of view that may cause incorrect cover/operation of the detector.
- Install the detector at proper height on a rigid surface. Do not install the detector on vibrating surface.

Technical specifications

| | |
|-------------------|-------------------------|
| Power supply | 24 VDC |
| Temperature | -20°C ~ 40°C |
| Humidity | < 93% |
| Range | 2-18 m (Adjustable) |
| Installing height | Max. 3.5 m |
| Power frequency | 5.8 GHz +/- 75MHz |
| Ambient light | 10~2000LUX (Adjustable) |
| Detection | 360 deg |

Terminals

| | | |
|--------------|--------|--------------|
| Power supply | + - | Power supply |
| Signal | + - | Output |

From:
<http://wiki.hiq-home.com/> -

Permanent link:
http://wiki.hiq-home.com/doku.php?id=en:ms_main:mw-a18-lc&rev=1590490238

Last update: **2020/05/26 10:50**

