

Motion sensor

Microwave detector on wall or ceiling



Model number:	MW-A18H-LC
Connects to:	digital input
Mounting:	High ceiling
Dimensions:	94mm x 42mm

Applications

- Motion detector
- Ready light
- Lighting control

Features

- Aestetical look
- Easy mount

Installation instruction

- Ensure that there are no obstructions (plants, screens, furniture etc.) in the field of view that may cause incorrect cover/operation of the detector.
- Install the detector at proper height on a rigid surface. Do not install the detector on vibrating surface.

Technical specifications

Power supply	24 VDC
Temperature	-20°C ~ 40°C
Humidity	< 93%
Range	2-18 m (Adjustable)
Installing height	Max. 10 m
Power frequency	5.8 GHz +/- 75MHz
Ambient light	10~2000LUX (Adjustable)
Detection	360 deg

Terminals

Common	-	-IN, -OUT
Signal	+	OUT+
Power supply	+	IN+

From:
<https://wiki.hiq-home.com/> -

Permanent link:
https://wiki.hiq-home.com/doku.php?id=en:ms_main:mw-a18h-lc&rev=1625295309

Last update: **2021/07/03 06:55**

